



Technical Service BULLETIN

March 13, 2003

Title:

HEADLIGHTS ON WITH SWITCH IN "OFF" POSITION

Models:

'03 Corolla & Matrix

ELECTRICAL
EL003-03

Introduction Some customers may complain that the headlights turn on with the switch in the "OFF" position while the vehicle is parked. This could result in a dead battery after an extended cold soak. An updated Headlamp Switch has been made available to address this situation.

- Applicable Vehicles**
- **2003** model year **Corolla** and **Matrix** vehicles produced before the VINs shown below.

Production Change Information

MODEL	PLANT	STARTING VIN
Corolla	Japan	JTDBR3#E#30025609
	NUMMI	1NXBR3#E#3Z123794
	TMMC	2T1BR3#E#3C743090
Matrix	TMMC	2T1##3#E#3C743090

Parts Information

PREVIOUS PART NUMBER	CURRENT PART NUMBER	PART NAME	QTY
84140-02170	Same	Switch, Headlamp (without Fog Lights)	1
84140-02200	Same	Switch, Headlamp (with Fog Lights)	1

Repair Procedure

1. Replace the Headlamp Switch.
2. Confirm proper headlight operation. If any of the three headlight modes (DRL/High/Low) are inoperative, refer to TSB EL001-03, "DRL Relay Check After Low/Dead Battery."

Warranty Information

OP CODE	DESCRIPTION	TIME	OFF	T1	T2
EL2007	R & R Headlamp Switch	0.3	84140-02170 84140-02200	82	73

Applicable Warranty*:

This repair is covered under the Toyota Comprehensive Warranty. This warranty is in effect for 36 months or 36,000 miles, whichever occurs first, from the vehicle's in-service date.

* Warranty application is limited to correction of a problem based upon a customer's specific complaint.

